

NEW**TP, Current transformers, split core**

Type	TP6	TP8
		
	width x height x depth (mm) 100 x 51 x 101.8	width x height x depth (mm) 138 x 51 x 154.8
ø (mm)	30	60
Flat strip(mm)	30x30	60x80
A	Class / VA 0.5 1 3 Code	Class / VA 0.5 1 3 Code
75/5	0 0 1 [*] M78011.	
100/5	0 0 1 [*] M78012.	0 0 1 [*] M78021.
150/5	0 0 1 [*] M78013.	0 0 1,5 [*] M78022.
200/5	0 0 2 [*] M78014.	0 0 1,5 [*] M78023.
250/5	0 1 2 [*] M78015.	0 1 2 [*] M78024.
300/5	0,5 1 2 [*] M78016.	0 1 2,5 [*] M78025.
400/5	1 2,5 4 [*] M78017.	1 1,5 3 [*] M78026.
500/5		2 5 7,5 [*] M78027.
600/5		2 5 8 [*] M78028.
700/5		2 5 8 [*] M78029.
750/5		2,5 5 10 [*] M7802A.
800/5		3 6 10 [*] M7802B.
1000/5		5 8 15 [*] M7802C.

For greater currents, use: transformer + transducer

Type	TP10	TP12
		
	width x height x depth (mm) 158 x 51 x 193.8	width x height x depth (mm) 190 x 66 x 244.8
ø (mm)	80	
Flat strip(mm)	80x120	80x160
A	Class / VA 0.5 1 3 Code	Class / VA 0.5 1 3 Code
500/5	0 4 12 [*] M78031.	
600/5	0 5 14 [*] M78032.	
750/5	3 6 17 [*] M78033.	
800/5	3 7 18 [*] M78034.	
1000/5	5 9 20 [*] M78035.	10 15 20 [*] M78041.
1200/5	6 11 24 [*] M78036.	
1250/5	7 15 28 [*] M78037.	
1500/5	8 17 30 [*] M78038.	15 20 25 [*] M78042.
1600/5	8 17 30 [*] M78039.	15 20 25 [*] M78043.
2000/5	8 17 30 [*] M7803A.	15 20 25 [*] M78044.
2500/5	8 17 30 [*] M7803B.	15 20 25 [*] M78045.
3000/5		20 25 30 [*] M78046.
4000/5		20 25 30 [*] M78047.
5000/5		20 25 30 [*] M78048.

For greater currents, use: transformer + transducer

TABLE OF ADDITIONAL FEATURES

TP									
M	7	X	X	X	X	0	0	X	
Code	Internal code						↑	Delivery time	
	Standard (.../ 5 A)						0	-	
Secondary	.../ 1 A						1	1	

Delivery time: [*] Immediate, [x] working weeks, [c] Consult